



# PCIe Asymmetric Breaker Modules

Automate hot-plug, dual redundancy and fault injection  
testing for PCIe devices

Quarch  
Data Sheet



# PCIe Asymmetric Breaker Modules

Automate hot-plug, dual redundancy and fault injection testing direct from a PCIe slot or HBA



## Highlights

- Supports the full range of PCIe devices
- Removes manual intervention, for fully automated testing
- Minimises adaptors needed, helping with Signal Integrity at Gen5 speeds
- Precise and consistent timing control over hot-swap scenarios
- Completely transparent at the protocol layer
- Supports power analysis (with additional equipment)
- Simple to control with your existing test automation system

## Use Cases

<b>System Qualification</b>	Run repeated test cycles with bounds testing of all possible hot-swap and lane width scenarios
<b>Regression Testing</b>	Automated regression tests spot issues earlier during development
<b>RAID Testing</b>	Force drive rebuilds, single/double RAID faults
<b>Failover Testing</b>	Test dual redundancy, fault monitoring and performance during a failure
<b>Fault Injection</b>	Simulate a large number of fault scenarios





---

## Hot Swap

PCIe data is switched with advanced high speed RF switches, ensuring that our modules are almost totally transparent to the storage system. Host/Device connections will appear as if they are directly attached.

Individual control over each pin allows us to create almost any possible hot-swap or fault scenario. Precise timing ensures that every test can be exactly re-created. Versions are available with inrush current limits, to help high power devices hot-plug on hosts with limited power supply capacity.

The modules can be manually controlled for bench testing, or easily integrated into your existing test automation system as part of a fully automated test solution.

---

## Module Range

Testing at Gen5 speeds can be difficult, as a single extra adaptor can add enough loss or cross-talk to disrupt the link. Asymmetric breakers allow for a wide range of tests to be performed direct from a PCIe slot, minimising the losses.

The modules also switch the PCIe lanes and have an additional injection port to allow power margining and measurement from our Programmable Power Module.

All modules support data rates up to 32GT/s.

Active signal driving is support for signals such as PERST, CLKREQ and WAKE. The exact signals driven varies from module to module

With the '+Triggering' option, sideband monitoring allows you to query the state of a sideband, or even diverly the state out of the triggering port, for easy connection to a scope or analyzer

Interface options depend on the controller you chose, but include simple Serial, USB and LAN options. These can be accessed from almost any scripting language. You will need to purchase a separate controller to use this module.

Drive modules can be combined with other Torridon modules as part of a full test-automation system.

---

## Supplied Parts

Each module comes with a 40cm interface cable, for connection to a controller.

---

## Also Required

**Controller** - You will require one slot on a Torridon Controller for each Cable Module or direct USB connection

**Downloads** - Our website contains many useful downloads to help you get started: [www.quarch.com](http://www.quarch.com)

- USB Drivers
- Technical Manuals
- Quick Start Guides
- Example Scripts
- TestMonkey GUI





## Support

Quarch provides direct support to all customers, regardless of the sales channel you use to purchase our equipment. We are available over email, or by phone during UK office hours. Our regional partners are also trained to handle many of the most common questions you might have.

Our support is normally free, though there may be charges if you require on-site training or significant development work. Please contact us if there is anything we can do to help.

Please see our website for access to drivers, technical manuals, quick-start guides, example scripts and more.

<b>Email</b>	<b>Phone</b>	<b>Web</b>
support@quarch.com	+44 1343 508 140	www.quarch.com/support

## Ordering

Quarch have a network of specialist partners around the world. Please contact our partner in your region if you require a quote.

We recommend evaluating our products before purchase, so our partners will be happy to arrange a free evaluation unit.

## Regional Contact Details

### North America

SerialCables LLC  
Colorado, California



Web [www.serialcables.com](http://www.serialcables.com)

### China, Hong Kong

Saniffer  
Hong Kong



Web [www.saniffer.com](http://www.saniffer.com)

### India

ESA Group  
Bangalore



Web [www.esaindia.com](http://www.esaindia.com)

### Taiwan

Reeper Technology  
Taipei



Web [www.reeper.com.tw/](http://www.reeper.com.tw/)

### Israel

EMY-Tech  
Misgav



Web [www.emy-tech.com](http://www.emy-tech.com)

### Europe and ROW

Quarch Technology  
Scotland, UK



Web [www.quarch.com](http://www.quarch.com)

### South Korea

JWill Technology  
Seoul



Web [www.jwill.co.kr](http://www.jwill.co.kr)

### ASEAN Countries

Gopalam Embedded Systems  
Singapore



Web [www.embeddedsingapore.com](http://www.embeddedsingapore.com)





## Products Versions

Product Code	Product Options
<b>QTLXXXX</b>	Product code, made up from options below
<b>QTL2804</b>	Gen5 MCIO x4 to U.2 Breaker
<b>QTL2805</b>	Gen5 MCIO x4 to U.2 Breaker + Triggering
<b>QTL2813</b>	Gen5 AIC x4 to U.2 Breaker
<b>QTL2814</b>	Gen5 AIC x4 to U.2 Breaker + Triggering
<b>QTL2826</b>	Gen5 AIC x16 to EDSFF Breaker
<b>QTL2827</b>	Gen5 AIC x16 to EDSFF Breaker + Triggering



AIC to U.2 Breaker Module





**Required Controllers** - One port on a controller is required for each module

Product Code	Description	
<b>QTL1260</b>	Torridon Interface Kit Simple USB and Serial control options for bench testing	
<b>QTL1461</b>	4 Port Torridon Controller Control up to 4 modules via Serial/LAN/USB connection	
<b>QTL1079</b>	28 Port Torridon Controller Control up to 28 modules via Serial, LAN or USB connection	

**Accessories**

Product Code	Description
<b>QTL999</b>	HD Programmable Power Module Power margining any uA range power measurement, ideal for PCIe devices
<b>QTL1558</b>	40cm Torridon Double Ended Interface Cable (Female to Female) Replacement cable for Card Modules, connects Module to Controller
<b>QTL1870</b>	100cm Torridon Double Ended Interface Cable (Female to Female) Replacement cable for Card Modules, connects Module to Controller
<b>QTL1381</b>	100cm Torridon Extension Cable (Male to Female) Extends an existing Double Ended Torridon cable or fixed Drive Module Cable





## Technical Information

Connections	QTL2804	QTL2805	QTL2813	QTL2814	QTL2826	QTL2827
-------------	---------	---------	---------	---------	---------	---------

Host Side Connector	MCIO	PCIe x4		PCIe x16		
Device Side Connector	U.2			EDSFF		
Max Speed	32GT/s					
Protocols	PCIe					
Signals Switched	All <sup>1</sup>					

<sup>1</sup>All power, high speed data, mated and sideband pins are individually switched. GND pins are directly routed through the module.

Control	QTL2804	QTL2805	QTL2813	QTL2814	QTL2826	QTL2827
---------	---------	---------	---------	---------	---------	---------

Power Supply	External PSU	Torridon Controller or external PSU				
Control Ports	Torridon Connector or direct USB					
Triggering	X	SMA	X	SMA	X	SMA
Power Injection Port	√	√	√	√	X <sup>1</sup>	X <sup>1</sup>

<sup>1</sup>PAM mezzanine can be optionally fitted to add power analysis

Dimensions	QTL2804	QTL2805	QTL2813	QTL2814	QTL2826	QTL2827
------------	---------	---------	---------	---------	---------	---------

Offsets Drive By	N/A	35.9mm		45mm		
Length/Width	133x135mm	PCIe HHHL		PCIe HHHL		
Height	-					
Compatible Devices	U.2			E1.x, E3.x		

Controllers	All Modules
-------------	-------------

Serial Control	Supported on all Controllers
USB Control	Supported on all Controllers and via direct USB cable
REST Control	Supported on QTL1079 and QTL1461
Telnet Control	Supported on QTL1079 and QTL1461





Features	QTL2804	QTL2805	QTL2813	QTL2814	QTL2826	QTL2827
<b>Basic (power) hot/swap</b>	√	√	√	√	√	√
<b>Full hot-swap</b>	√	√	√	√	√	√
<b>Pin Bounce Simulation</b>	1uS minimum period					
<b>Signal Glitch</b>	Single/Cycle/PRBS					
<b>Voltage Monitoring</b>	√	√	√	√	√	√
<b>Power Monitoring</b>	Requires HD Power Module				√ <sup>1</sup>	√ <sup>1</sup>
<b>Active Signal Driving</b>	PERST, PERSTB, DUALPORTEN, PWR_DIS, HPT0, HPT1		PERST, PERSTB, DUALPORTEN, WAKE, PWR_DIS, HPT0, HPT1		PERST, PERSTB, PRSNT1, PRSNT2, PWR_DIS, SMBRST, LED, DUALPORTEN	
<b>Signal Monitoring</b>	All low speed sidebands		All low speed sidebands		All low speed sidebands	

<sup>1</sup> PAM mezzanine can be optionally fitted to add power analysis

Features...	QTL2804	QTL2805	QTL2813	QTL2814	QTL2826	QTL2827
<b>Basic (power) hot/swap</b>	√	√	√	√	√	√
<b>Full hot-swap</b>	√	√	X	√	√	√
<b>Pin Bounce Simulation</b>	1uS minimum period		X	1uS minimum period		
<b>Signal Glitch</b>	Single/Cycle/PRBS		X	Single/Cycle/PRBS		
<b>Voltage Monitoring</b>	√	√	√	√	√	√
<b>Power Monitoring</b>	X	X	X	X	X	X
<b>Active Signal Driving</b>	PERST, DUALPORT, IF_DET, PWR_DIS, PRSNT, HPT0, HPT1		PRSNT, PERST, PERSTB, DUALPORTEN, PWRDIS, IFDET, IFDET2, HPT0, HPT1		PRSNT0, PERST0, SMBRST, PWRDIS, MFG, DUALPORTEN	
<b>Signal Monitoring</b>	PERST, PERSTB, SMCLK, SMDAT, DUALPORT, IF_DET, ACTIVITY, WAKE, PWR_DIS, PRSNT, HPT0, HPT1		PERST, PERSTB, SMBCLK, SMBDAT, DUALPORT, IF_DET, IFDET2, HPT0, HPT1, PRSNT, WAKE, PWRDIS		PRSNT0, PERST0, SMBRST, SMBCLK, SMBDAT, PWRDIS, MFG, DUALPORTEN	



